Hydraulic Power Pack with Under Oil Motor

SPA 01

Q_{max} 10 l/min • p_{max} 250 bar • P_{max} 3 kW

Example: plastic tank version

Technical Features



Example: steel tank version additional valves in stacking assembly



- > AC electro-hydraulic compact unit with under oil motor
 - Compact design with reduced overall dimensions for production cost saving
- > Main applications are lifting platforms
- > 3 central block basic circuits option
- > Possibility of building up an additional circuit in the form of vertical or horizontal stacking assembly
- > One- and three-phase motors with power ratings of up to 3 kW
- > Tank capacities from 7 to 30 I with optional plastic tanks for cost saving
- In the standard version, the aluminium basic block is without surface protection and steel plate are zinc coated for 240 h protection acc. to ISO 9227

Functional Description

The under oil power packs are designed for applications which require low noise levels as well as small envelope dimensions. They are designed to operated only occasionally, thus being suitable mainly for the use in lifting platforms, elevating tables and handling devices. Each power pack consists of an electric motor, a pump, a manifold and a tank. The aluminum body forms the base of the power pack, on which all the main components, including the hydraulic elements, are mounted. The function of the power packs is apparent from the respective hydraulic circuit diagrams. The desired combination of particular components and hydraulic elements can be defined by reference to the ordering code and the respective tables. The additional hydraulic circuits can be built up valve sizes 03 (RPEK), 04 (CETOP 02) and 06 (CETOP 03). The size 03 (RPEK) is in the form of a sectional directional valve.

The mounting position of the power pack is horizontal - see Power Pack Dimensions. The basic combinations of electric motors and pumps, as well as their code designations, are shown in table 1.

Technical Data

Flow rate	l/min	see tab	e 1		
Working pressure	bar	see tab	e 1		
Max. operating pressure	bar	see tab	e 1		
Tank capacity		7, 10, 20), 30		
Type of hydraulic pump		Gear pump, Cl	Gear pump, CLOCKWISE		
Electrical Motor power ratings	kW	0.55 - 3			
Type of electric motor		one- and three	ee-phase		
Voltage of electric motor	V AC	230	400		
Duty cycle S3 of electric motor	%	20			
Frequency	Hz	50			
Protection degree of power unit		IP 55			
Viscosity range	mm²/s	20 100			
Fluid temperature range	°C	-20 +	-80		
Ambient temperature max.	°C	+50			
Thread of functional ports P, T, M		G1/4	ļ		
	Datasheet	Туре	Туре		
General information	GI_0060	Products and opera	Products and operating conditions		

Ordering Code

		SPA	01 -	/	-]-[-		/				
Under	oil power pack									—			Solenoid voltage
Bump	displacement ir	cm ³								01200	12 V DC		60 V DC
0.8	08	3.6	36							01400	14 V DC	10200	102 V DC
1.2	12	4.4	44							02100	21 V DC	20500	205 V DC
1.6	16	4.8	48							02400	24 V DC		24 V / 50 (60) HZ
2.1	21	5.8	58								42 V DC		115 V / 50 (60) HZ
2.5	25	6.2	62							04800	48 V DC	23050	230 V / 50 (60) HZ
3.3	33	7.9	79										
Carlas	6 4 h a . a l a aduit a			1						Nomina	l size of s	tacking a	assembly elements
Code o	f the electric mo	otor on reque	st! - see table	1					0			witho	ut stacking assembly
Start-u	p module								3				size 03
	start-up module	2		0					4				size 04
	rt-up module	-		М					6				size 06
Type o	f the block - see	e page 3										Numb	er of add-on units
		1 3						0				witho	ut stacking assembly
Code c	f the tank							1					1 section
7						7		2					2 sections
10 l						10		3					3 sections
20 I						20		4					4 sections
30 I						30		5					5 sections





Tab. 1a

			Code of the pump						
Code of the electric motor on request!		08 GP1	12 GP1	16 GP1	21 GP1	25 GP1	33 GP1		
p _{max} ** [bar]			250						
rpm [1/min]	400 V AC	kW	Q/p _N *[l/min]						
1500	13	0.55		1.5/175	2.0/130	2.6/100	3.1/85	4.2/65	
	14	0.75			1.9/190	2.5/145	3.0/120	3.9/90	
	15	1.10			2.1/200	2.8/190	3.3/160	4.4/120	
	16	1.50					3.2/200	4.2/170	
	17	2.20							
	18	3.0							
3000***	30	0.55	2.2/120	3.2/80	4.3/60	5.6/45	6.7/40	8.9/30	
	31	0.75	2.2/160	3.2/110	4.3/80	5.6/65	6.7/55	8.9/40	
	32	1.10	2.2/200	3.2/165	4.3/120	5.6/95	6.7/80	8.9/60	
	33	1.50		3.2/200	4.3/165	5.6/130	6.7/110	8.9/80	
	34	2.20			4.2/200	5.5/190	6.6/160	8.7/120	
	35	3.00					6.4/200	8.5/170	
rpm [1/min]	230 V AC	kW	Q/p _N *[l/min]	/[bar]					
	5	0.55		1.6/165	2.1/125	2.7/100	3.2/80	4.3/60	
1500	6	0.75		1.6/200	2.1/170	2.8/130	3.3/110	4.4/80	
1500	7	1.10				2.8/190	3.3/160	4.4/120	
	8	1.50					3.3/200	4.4/165	

Tab. 1b

Code of the electric motor on request! p _{max} ** [bar]			Code of the pump							
			36 GP1	44 GP1	48 GP1	58 GP1	62 GP1	79 GP1		
			250			200	160			
rpm [1/min]	400 V AC	kW	Q/p _N *[l/min]	Q/p _N *[l/min]/[bar]						
1500	13	0.55	4.5/60	5.5/50	6.0/45	7.3/35	7.8/35	9.9/25		
	14	0.75	4.3/85	5.2/70	5.7/65	6.9/50	7.4/50	9.4/40		
	15	1.10	4.8/110	5.8/90	6.3/85	7.7/70	8.2/65	10.4/50		
	16	1.50	4.6/155	5.6/130	6.2/115	7.4/100	8.0/90	10.1/70		
	17	2.20		5.0/200	5.5/190	6.6/160	7.1/150	9.0/120		
	18	3.00			5.9/200	7.1/200	7.6/180	9.7/150		
3000***	30	0.55								
	31	0.75	9.7/35							
	32	1.10	9.7/55	11.8/45	12.9/40	15.6/35				
	33	1.50	9.7/75	11.8/60	12.9/55	15.6/45	16.7/40			
	34	2.20	9.5/110	11.6/90	12.7/85	15.3/70	16.4/65	20.9/50		
	35	3.00	9.3/155	11.3/125	12.4/115	15.0/95	16.0/90	20.4/70		
rpm [1/min]	230 V AC	kW	Q/p _s *[l/min]/[bar]							
1500	5	0.55	4.7/55	5.7/45	6.2/40	7.5/35	8.0/30	10.2/25		
	6	0.75	4.8/75	5.9/60	6.4/55	7.7/45	8.3/45	10.5/35		
	7	1.10	4.8/110	5.9/90	6.4/80	7.7/70	8.5/65	10.5/50		
	8	1.50	4.8/150	5.9/120	6.4/110	7.7/95	8.5/85	10.5/70		

 $p_{\rm N}^{\rm N}$ - nominal pressure = the highest working pressure allowed without time restriction ** $p_{\rm max}$ - maximum pressure = maximum pressure allowed for a short time - max. 20 s ***Before motor selection contact the producer.

AC Motors	3-phase	1-phase
Phase-connections for correct direction of motor rotation	$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	L1 N W2 U2 V2 U2 U2 U1 V1 W1

A R G O HYTOS A Voith Company

Type of the Block



The hydraulic circuit S11.X enables the power pack to be used as a simple pressure supply for general applications with the possibility to build up additional hydraulic circuits in the form of horizontal stacking assemblies of the size 04 or 06 (S11.0) or size 03 (S11.1). **The hydraulic circuits S14.N** and **S24.N** enable the power pack to be used as pressure supply for lifting platforms and other devices, in which the

weight of the system provides returning into the basic position. The shuf-off valve (A) enables emergency lowering of the device, should a disconnection of the supply voltage occur.

The hydraulic circuit S14.N comprises a flow control valve VSK (B) which is adjustable only in a certain range (see cataloge VSK - HA 5121). This valve is accessible from outside of the block. If not otherwise required, a valve VSK is mounted into the block. The stabilized flow rate of this valve corresponds with the respective flow rate of the power pack (see Tab. 1).

The hydraulic circuit S24.N comprises a throttle valve VSV1-06 (C) without pressure compensation. This valve is accessible from outside of the block. M - start-up module is suitable for one-phase E-motors (codes 5-9).

Use it if there is no possibility to unload the pressure in the circuit.





Code of the tank	Tank Capacity [I]	Working volume [l]	A1 [mm]	A2 [mm]	A3 [mm]	A4 [mm]
10 (steel)	10	6	440	220	220	180
20 (steel)	20	10	500	220	260	222
30 (steel)	30	20	500	220	260	302



000

iensions in millimeters (inches)

Plastic tank

CAUTION!

Plastic tanks are not UV stable. Place the unit in the shade for outdoor application. Highly recommended mounting position for units with tank code 7. Use steel bracket for hanging position. Plastic tank may be deformated (creep) while standing on plastic foots only due to weight, temperatures, UV light exposition and aging.



Example of horizontal stacking assembly

- possible only with hydraulic circuit \$11.0
- E according to the elements used, see datasheet of modular elements HA 5021, HA 5023, HA 5051, HA 5093
- F Size 04=40 mm Size 06=50 mm
- G- Size 04=79 mm Size 06=92 mm



- possible only with hydraulic circuit S11.1

